










Satellite Dish Antenna

AD60-W5

Reflector		
Steel Thickness	0.6mm	
Parameter	a=600,b=660,f=360.2,f/d=0.6	
Material	Q195A (
Bottom Hole Diameter	4-Φ8	
Installing Hole distance	156×142mm	
Weight Kgs	1.85kg	
Back bracket		
Steel Thickness	2mm	
Outline Dimensions	182×167×70.5mm	
Material	Q195A (
Bottom Hole Diameter	4-Φ8	
Installing Hole distance	156×142mm	
Inside dimension	85mm	
Feedhorn supporter Installing Hole	2-M6	
Feedhorn supporter Installing Hole distance	125mm	
Weight Kgs	0.45kg	

Adjustive clamp		
Steel Thickness	2mm	
Outline Dimensions	84×81×76mm	
Material	Q195A (DC01)	
Bottom Hole Diameter	6-M6	
Installing Hole distance	60mm	
Inside dimension	80mm	
Scale adjustment	0-90°	
Weight Kgs	0.23kg	
Feedhorn supporter		
Steel Thickness	19×1mm	
Back bracket Installing Dimension	378mm	
Feedhorn Installing Dimension	437mm	
Material	Q195A-Welded pipe	
Back bracket Installing Hole	2-Φ6.5	
Back bracket Installing Hole distance	125mm	
LNB Holder Side Hole LNB	6.5x6.5	
Angle	R41	
Angle	78.2°±0.2°	
Weight Kgs	0.45kg	
Pipe clamp		
Steel Thickness	2mm	
Outline Dimensions	84.5x75x23mm	
Material	Q195A (DC01)	
Installing Hole distance	60mm	
Installing Hole	2-Φ7	
Weight Kgs	0.13kg	
Pole component		
Steel Thickness	1mm	
Outer Diameter	Φ32mm	
Material	Q195A	
Length	400mm	
Height	300mm	
Angle	R105	
Angle	90°±1°	
Weight Kgs	0.7kg	
LNB supporter		
Total Dia for LNB	Φ40mm	
Slot Size for fitting on LNB Arm	19.4mm	
Width	24.6mm	
Square Hole Size	6.5×6.5mm	
Weight Kgs. including Nut	0.03kg	